



RoLP Solista

STANDARD SOUNDER WITH LED

The use of beacons to supplement audible alarms is becoming increasingly common. A combined sounder beacon allows both an audible and visual alarm to be provided but requires only a single installation point. LED beacons have a dramatically lower current consumption than that of traditional xenon beacons making them ideal for applications where sounder circuit capacity is limited.

- ULTRA LOW CURRENT – LED TECHNOLOGY
- SOUNDER & BEACON WITH A SINGLE INSTALLATION POINT
- UNOBTRUSIVE LOW PROFILE DESIGN
- STANDARD FULLEON BASE SIMPLIFIES SYSTEM UPGRADES
- LOCKABLE BASE

Specification

| | |
|----------------|---------------------------|
| Voltage | 9 - 28Vdc (*1) |
| Current | 19mA (Typical Tone 3) |
| Sound Output | 101dB(A) (Typical Tone 3) |
| Tones | 32 |
| Light Output | > 0.5Cd |
| Flash Rate | 1Hz |
| Volume Control | 20dB |
| Monitoring | Reverse polarity |
| Temperature | -10°C to +55°C |
| Protection | IP54 (s)* IP65 (d)* |
| Construction | ABS, PC lens |
| Weight | 0.3Kg |
| Colours | Red or white |
| Flash Colour | Red |

(*1) 110 to 230Vac with powered base

(s)* Shallow Base

(d)* Deep / U Base